

Release note for *dCS* Remote v2.10 for Pronto TSU3500 & RU960

What's new?

The v2.10 configurations for the TSU3500 & RU960 handsets have the following changes to give similar functionality to the v2.10 configuration for the TSU9400 handset:

- All controls are now on one or two pages per device, for quicker navigation. A few redundant commands have been omitted (e.g. **CD/SACD** is present, but there are no longer separate **CD** & **SACD** buttons).
- The 4 black buttons just below the screen are programmed to jump to page 1 of the four devices, as indicated by the labels (NOT touch buttons!) at the bottom of the screen: **DAC**, **CD** (Transport), **Clock** and **Ups** (Upsampler). These wake up the handset and select the required device with one touch.
- The **HOME** page has a second page containing 7 macros for automated set-up of a 4-box Scarlatti or Paganini system to the most common settings:
 - Upsampling data on the Upsampler's **AES** input to **24/176.4** or **DSD**
 - Upsampling data on the Upsampler's **RCA1** input to **24/176.4** or **DSD**
 - Upsampling data on the Upsampler's **USB** input to **24/176.4**, **24/192** or **DSD**Please make sure that the DAC, Upsampler and Clock can "see" the Pronto for about 5 seconds after pressing one of the macro buttons, otherwise some of the commands may not be received and the set-up will be incomplete.
- **DAC** page 2 has a third sync source button – Sync to Word Clock (**WCik**). Updated software for the Scarlatti DAC and Paganini DAC that responds to this button will be released soon - v1.10.
- Note that the Upsamplers cannot be set to output 32k unless they are locked to 32k.

Updating procedure

The new configuration file can be loaded into the handset as follows:

- A Windows 98/Me/2000/XP computer is required.
- Connect your handset to the computer with a USB cable.
- Run the loader program which matches the model of your handset: **dCS remote_2V10_RU960.exe** for RU960 or **dCS remote_2V10_TSU3500.exe** for TSU3500.
- Click on the Download button, wait about 15 seconds while the configuration is downloaded.
- Disconnect the handset and check it is working correctly.

The configuration file (.pcf) is also supplied, in case you want to modify them with ProntoEdit NG (which can be downloaded from www.pronto.philips.com/). Sorry, we cannot offer help with this – please consult the Philips ProntoEdit manual or an experienced installer.

We hope that you find the macros useful and the new arrangement easy to use.

dCS May 2010