

dCS Lina IR Codes

The IR receiver on the Lina DAC is active on software version 2.0 and forwards. When the IR setting on the DAC is set to Generic, the DAC uses the modified NEC IR code base as used by Apple TV remote controls (as opposed to the RC code base used with the dCS Universal Remote).

The Generic IR setting shows as the following icon on the front panel menu of the Lina DAC: 

The following NEC codes are used on the generic setting:

- Up (0x05) – volume up
- Down (0x06) – volume down
- Left (0x04) – for navigating the menu
- Right (0x03) – for navigating the menu
- Menu (0x01) – to enter or leave the menu
- Select (0x2E followed by 0x02) – to select menu items, or mute on status screen
- Play/Pause (0x2F followed by 0x02) – Play/Pause when playing from network

Copyright © 2023 Data Conversion Systems Limited. All rights reserved.

dCS, dCS Expanse, dCS logo, Ring DAC are trademarks or registered trademarks of Data Conversion Systems Limited. Data Conversion Systems Limited disclaims any proprietary interest in trademarks and trade names other than its own. All specifications are subject to change and, whilst they are checked for accuracy, no liabilities can be accepted for errors or omissions.

Apple, the Apple logo, iPhone, iPod and iPad are trademarks of Apple Inc., registered in the U.S. and other countries and regions. App Store is a service mark of Apple Inc.

Android, Google Play and the Google Play logo are trademarks of Google LLC.

iOS is a trademark or registered trademark of Cisco in the U.S. and other countries and is used under license.

Data Conversion Systems Ltd.
Unit 1, Buckingham Business Park, Anderson Road, Swavesey,
Cambridgeshire. CB24 4AE UK

dcsaudio.com